



Function		Jumper	Position
»	Factory configured - do not alter	J2	Open
»	CMOS memory normal operation	JP16	pins 1 & 2 closed
	CMOS memory clear	JP16	pins 2 & 3 closed
»	Monitor type select color	JP17	Closed
	Monitor type select monochrome	JP17	Open
»	Factory configured - do not alter	JP19	Open
»	Factory configured - do not alter	JP26	Open
»	Factory configured - do not alter	JP30	Open
»	Factory configured - do not alter	JP31	Open
»	Factory configured - do not alter	JP42	Open

#### DRAM CONFIGURATION

Size	Bank 0	Bank 1	Bank 2	Bank 3
1MB	(1) 256K x 36	NONE	NONE	NONE
2MB	(1) 256K x 36	(1) 256K x 36	NONE	NONE
2MB	(1) 512K x 36	NONE	NONE	NONE
4MB	(1) 512K x 36	(1) 512K x 36	NONE	NONE
4MB	(1) 1M x 36	NONE	NONE	NONE
4MB	(1) 256K x 36	(1) 256K x 36	(1) 512K x 36	NONE
5MB	(1) 256K x 36	(1) 1M x 36	NONE	NONE
6MB	(1) 256K x 36	(1) 256K x 36	(1) 1M x 36	NONE
6MB	(1) 512K x 36	(1) 1M x 36	NONE	NONE
8MB	(1) 256K x 36	(1) 256K x 36	(1) 512K x 36	(1) 1M x 36
8MB	(1) 512K x 36	(1) 512K x 36	(1) 1M x 36	NONE

8MB	(1) 1M x 36	(1) 1M x 36	NONE	NONE
8MB	(1) 2M x 36	NONE	NONE	NONE
10MB	(1) 256K x 36	(1) 256K x 36	(1) 1M x 36	(1) 1M x 36
12MB	(1) 512K x 36	(1) 512K x 36	(1) 1M x 36	(1) 1M x 36
12MB	(1) 1M x 36	(1) 1M x 36	(1) 1M x 36	NONE
16MB	(1) 2M x 36	(1) 2M x 36	NONE	NONE
16MB	(1) 1M x 36	(1) 1M x 36	(1) 1M x 36	(1) 1M x 36
16MB	(1) 4M x 36	NONE	NONE	NONE
17MB	(1) 256K x 36	(1) 4M x 36	NONE	NONE
18MB	(1) 256K x 36	(1) 256K x 36	(1) 4M x 36	NONE
20MB	(1) 512K x 36	(1) 512K x 36	(1) 4M x 36	NONE
20MB	(1) 1M x 36	(1) 4M x 36	NONE	NONE
24MB	(1) 2M x 36	(1) 2M x 36	(1) 2M x 36	NONE
24MB	(1) 512K x 36	(1) 512K x 36	(1) 1M x 36	(1) 4M x 36
24MB	(1) 1M x 36	(1) 1M x 36	(1) 4M x 36	NONE
32MB	(1) 2M x 36	(1) 2M x 36	(1) 2M x 36	(1) 2M x 36
32MB	(1) 4M x 36	(1) 4M x 36	NONE	NONE
32MB	(1) 8M x 36	NONE	NONE	NONE
36MB	(1) 512K x 36	(1) 512K x 36	(1) 4M x 36	(1) 4M x 36
36MB	(1) 1M x 36	(1) 4M x 36	(1) 4M x 36	NONE

**DRAM CONFIGURATION (CON'T)**

<b>Size</b>	<b>Bank 0</b>	<b>Bank 1</b>	<b>Bank 2</b>	<b>Bank 3</b>
36MB	(1) 1M x 36	(1) 8M x 36	NONE	NONE
40MB	(1) 1M x 36	(1) 1M x 36	(1) 4M x 36	(1) 4M x 36

40MB	(1) 1M x 36	(1) 1M x 36	(1) 8M x 36	NONE
48MB	(1) 4M x 36	(1) 4M x 36	(1) 4M x 36	NONE
48MB	(1) 4M x 36	(1) 8M x 36	NONE	NONE
64MB	(1) 4M x 36	(1) 4M x 36	(1) 4M x 36	(1) 4M x 36
64MB	(1) 16M x 36	NONE	NONE	NONE
64MB	(1) 4M x 36	(1) 4M x 36	(1) 8M x 36	NONE
64MB	(1) 8M x 36	(1) 8M x 36	NONE	NONE
65MB	(1) 256K x 36	(1) 16M x 36	NONE	NONE
68MB	(1) 1M x 36	(1) 16M x 36	NONE	NONE
68MB	(1) 1M x 36	(1) 8M x 36	(1) 8M x 36	NONE
72MB	(1) 1M x 36	(1) 1M x 36	(1) 16M x 36	NONE
72MB	(1) 1M x 36	(1) 1M x 36	(1) 8M x 36	(1) 8M x 36
80MB	(1) 4M x 36	(1) 16M x 36	NONE	NONE
80MB	(1) 4M x 36	(1) 8M x 36	(1) 8M x 36	NONE
96MB	(1) 4M x 36	(1) 4M x 36	(1) 16M x 36	NONE
96MB	(1) 4M x 36	(1) 4M x 36	(1) 8M x 36	(1) 8M x 36
96MB	(1) 8M x 36	(1) 8M x 36	(1) 8M x 36	NONE
128MB	(1) 16M x 36	(1) 16M x 36	NONE	NONE
128MB	(1) 8M x 36	(1) 8M x 36	(1) 8M x 36	(1) 8M x 36

CACHE CONFIGURATION			
Size	Bank 0	Bank 1	TAG
128KB	(4) 32K x 8	NONE	(1) 8K x 8
256KB	(4) 32K x 8	(4) 32K x 8	(1) 32K x 8
256KB	(4) 64K x 8	NONE	(1) 32K x 8

512KB	(4) 64K x 8	(4) 64K x 8	(1) 32K x 8
512KB	(4) 128K x 8	NONE	(1) 32K x 8

CACHE JUMPER CONFIGURATION					
Size	JP1	JP2	JP4	JP40	JP41
128KB	1 & 2	1 & 2	1 & 2	1 & 2	1 & 2
256KB	2 & 3	2 & 3	1 & 2	2 & 3	2 & 3
256KB	1 & 2	2 & 3	1 & 2	1 & 2	1 & 2
512KB	2 & 3	2 & 3	2 & 3	2 & 3	2 & 3
512KB	1 & 2	2 & 3	2 & 3	1 & 2	1 & 2

Note: Pins designated should be in the closed position.

CPU TYPE CONFIGURATION						
Type	JP8	JP9	JP11	JP12	JP14	JP15
80486SX	2 & 3	Open	Open	3 & 4	2 & 3	4 & 5
CX486DX	1 & 2	Closed	2 & 3	2 & 3	1 & 2, 3 & 4	2 & 3
80486DX	1 & 2	Closed	2 & 3	3 & 4	2 & 3	4 & 5
80486DX2	1 & 2	Closed	2 & 3	3 & 4	2 & 3	4 & 5

Note: Pins designated should be in the closed position.

CPU TYPE CONFIGURATION (CON'T)					
Type	JP21	JP22	JP24	JP25	JP46
80486SX	2 & 3	1 & 2	Open	Open	2 & 3
CX486DX	1 & 2	2 & 3	2 & 3	2 & 3	1 & 2
80486DX	2 & 3	1 & 2	Open	Open	2 & 3
80486DX2	2 & 3	1 & 2	Open	Open	2 & 3

Note: Pins designated should be in the closed position.

#### CPU SPEED CONFIGURATION

Speed	JP5	JP6	JP7	JP20
20MHz	Closed	Open	Closed	pins 1 & 2 closed
25MHz	Closed	Closed	Open	pins 1 & 2 closed
33MHz	Open	Closed	Closed	pins 1 & 2 closed
40MHz	Closed	Open	Open	pins 2 & 3 closed
50MHz	Closed	Closed	Open	pins 1 & 2 closed
66MHz	Open	Closed	Closed	pins 1 & 2 closed

#### BUS SPEED CONFIGURATION

CPU speed	JP29
<=33MHz	pins 1 & 2 closed
>33MHz	pins 2 & 3 closed

#### VESA WAIT STATE CONFIGURATION

Wait states	JP28
0 wait states	pins 1 & 2 closed
1 wait state	pins 2 & 3 closed